

Ohme ePod Mounting post installation guide



Installation guide

We recommend a 400mm x 400mm x 300mm (depth) concrete foundation to be set into the ground

Set twin wall ducting into the centre of the foundation, to allow for cabling entry into the post

When positioning the post onto the foundation, feed the cabling up through the post and out the slot/hole on the front face (below the charger unit backplate)

Fix the post down using M10 through bolts, and then use black bolt caps to cover the fixings

Features and specifications

Colour:

Zinc primed + RAL 9005 satin black

Construction:

3mm carbon steel, plastic top insert

Cable management:

Internal access holes fitted with blind grommets

Dimensions (mm):

1300 (H) x 60 (W) x 60 (D)

200 X 200 x 8 (base plate)

170 Bolt fixing centres

Warranty:

2 Years

Fixings base:

X4 M10x86 zinc plated through bolts

